

# On the stabilizability and controllability of a degenerate differential system in Banach spaces

Nor-El-Houda Beghersa

Departement of Mathematics, Faculty of Mathematics and Computer Sciences, University of Sciences and Technology of Oran Mohamed Boudiaf USTO-MB, El Mnaouar, BP 1505, Bir El Djir, 31000, Oran, Algeria

*norelhouda.beghersa@univ-usto.dz*

April 6, 2023

# Plane of work

# Introduction

The fundamental challenges of mathematical problems about differential systems appears precisely in control theory, many researchers use linear systems of two types: continuous or discrete. Since 1970, many mathematicians become interested in another wide classes of differential systems which have a real practical and physical applications can be found in [?, ?, ?, ?].

In the present paper, we propose the problem differential of implicit stationary equation described as follows:

$$Ax'(t) = Bx(t) + \varphi(t, x(t)), \quad t \geq 0; \quad (1)$$

with initial condition

$$x(t_0) = x_0.$$

Here, we assume that  $A$  and  $B$  are two bounded linear operators acting in the same complex Hilbert space  $\mathcal{H}$  and  $\varphi$  is a continuous function from  $[0, \infty[ \times \mathcal{H}$  into  $\mathcal{H}$ , the operator  $A$  is not invertible.

# Introduction

We need those notations:  $\|\cdot\|$ ,  $\langle \cdot, \cdot \rangle$  are the norm and the inner product in  $\mathcal{H}$ . Now, we consider the system (??) in the homogenous case and suppose that it has a solution then:

- The system (??) is said to be exponential, if for any solution  $x(t)$  with  $t \geq 0$ , we have

$$\|x(t)\| \leq Me^{\alpha t} \|x_0\|, \quad t \geq 0; \quad (2)$$

where the constants  $\alpha$  and  $M$  are not depended on the solution  $x(t)$ .

- For  $\alpha < 0$ , the system (??) is exponentially stable. In particular, for  $\alpha = 0$  it is uniformly bounded.
- The system (??) is well-posed, if it satisfies the following conditions:
  - 1 If for any solution  $x(\cdot)$  such that  $x(0) = x_0$ , then  $x(t) = 0$  for all  $t \geq 0$ ;
  - 2 it generates an evolution semigroup of bounded operators  $S(t) : x_0 \mapsto x(t)$  for all  $t \geq 0$ .

The operators  $S(t)$  are defined on the set  $D_0 = \{x_0\}$  of the admissible initial vectors  $x_0$ .

# Lyapunov's theorem and its generalization

In this section, we investigate the homogeneous problem of Eq.(??) with  $\varphi \equiv 0$  in the next form:

$$Ax'(t) = Bx(t), \quad t \geq 0, \quad x(t_0) = x_0; \quad (3)$$

our main objective is to extend the general Lyapunov theorem [?] of the linear differential systems to the operator pencil  $\lambda A - B$  then, we apply the achieved results to affirm the stability and controllability of some degenerate systems as Eq.(??).

## Definition

[?] The complex parameter  $\lambda$  is said to be regular point of the pencil  $\lambda A - B$ , if the operator  $(\lambda A - B)^{-1}$  exists and it is bounded in  $\mathcal{H}$ . We denote by  $\rho(A, B)$  the set of all regular points and its complement by  $\sigma(A, B) = \mathbb{C} \setminus \rho(A, B)$ , which is also called the spectrum of the operator pencil  $\lambda A - B$ . The set of all eigen-values of the pencil  $\lambda A - B$  is denoted by  $\sigma_p$ , such that

$$\sigma_p(A, B) = \{\lambda \in \mathbb{C} \mid \exists v \neq 0, (\lambda A - B)v = 0\}.$$

# Lyapunov's theorem and its generalization

## Theorem

Consider the problem (??). If the spectrum  $\sigma(A, B)$  of the linear bounded operators  $A$  and  $B$  lies in the left half plane ( $\text{Re}(\lambda) < 0$ ), then for any uniform positive operator  $G \gg 0$ , there exists a uniform positive operator  $W \gg 0$  such that

$$B^*WA + A^*WB = G. \quad (4)$$

## Theorem

If Eq.(??) is satisfying for the pair  $(W, G)$  of bounded positive uniform operators, then  $i$  is not an eigen-value for the operator pencil  $\lambda A - B$ .

We recall some notes concerning uncontrollable system as (??) before summarizing our results. Let  $D_0 = \{x_0\}$  be the initial subspace of  $\mathcal{H}$ , we denote by  $A_0 = A|_{D_0}$  the invertible restriction of the operator  $A$  in  $D_0$  (The operator  $A_0$  is invertible, if the system (??) is well-posed).

## Lemma

Let  $A_0$  be an invertible operator. If  $\varphi(\tau, x(\tau)) \in AD_0$  for any  $\tau \geq \tau_0$  and the function  $S(t - \tau)A_0^{-1}\varphi(\tau, x(\tau))$  is integrable (with respect to  $\tau$ ) where  $\{S(t)\}_{t \geq 0}$  is the semigroup of the operators of Eq.(??), then the system (??) is equivalent to the following equation:

$$x(t) = S(t)x_0 + \int_0^t S(t - \tau)A_0^{-1}\varphi(\tau, x(\tau))d\tau. \quad (5)$$

# Lyapunov's theorem and its generalization

## Lemma

See([?]) If  $g(t) \leq c + \int_0^t g(\tau)h(\tau)$  for all  $t \geq 0$ , where  $h$  is a continuous positive real function and  $c > 0$  is an arbitrary constant, then

$$g(t) \leq c \cdot \exp\left(\int_0^t h(\tau) d\tau\right).$$

## Theorem

Suppose that:

- 1 the system (??) is well-posed;
- 2 the linear operator  $\varphi(t, x(t))$  transforms  $D_0$  into  $AD_0$  such that

$$\int_0^{\infty} \|A_0^{-1}\varphi(t, x(t))\| dt < \infty, \quad \forall t \geq 0;$$

then the system (??) is exponentiall stable.

# Lyapunov's theorem and its generalization

Particularly, in finite dimensional spaces we can use the theory of elementary divisors of the matrix pencil  $\lambda A - B$  for example see [?], we establish the next important result.

## Theorem

*The following statement are equivalent:*

- 1 *The system (??) is exponentially stable;*
- 2  $\sigma(A, B) = \sigma(A, B) \subset \{\lambda : \operatorname{Re}(\lambda) < 0\};$
- 3 *There exists a positive definite matrix  $W \gg 0$  such that  $B^*WA + A^*WB \gg 0.$*

In finite dimensional spaces, exponential stability is characterized by the fact that the spectrum of matrices  $A$  and  $B$  lies in the left half plane, but the situation in infinite dimensional spaces is much more complicated.

# Relation between stabilizability and controllability

We provide here some definition and basic reluts about the exact controllability and complete stabilizability of an implicit differential control system governed by the general form:

$$Ax'(t) = Bx(t) + Cu(t), \quad x(0) = x_0. \quad (6)$$

where  $C$  is also a linear bounded operator and  $u(t)$  is a function takes values in the Hilbert space  $U \subset \mathcal{H}$  supposed to be Bockner integrable.  $x(t)$  is the mild solution for restriction on a class of controls  $u$  given by

$$x(t) = x(t, u(\cdot), x_0) = S(t)x_0 + \int_0^t S(t - \tau)A_0^{-1}Cu(\tau)d\tau. \quad (7)$$

# Relation between stabilizability and controllability

The famous relation between exact controllability and complete stabilizability was first established by Slemrod who proved that the controllability from any state to any state implies the exponential stabilizability. In [?] Zabczyk showed that the implication in the opposite way is possible, some authors precised that in the case of Hilbert spaces with bounded operators the previous idea is not available.

The system (??) is exactly cotrollable if for all  $x_0, x_1 \in \mathcal{H}$ , there exists a time  $T$  and a control  $u \in L_p(0, T; U)$ ,  $p \geq 1$ , such that  $x(T, u(\cdot), x_0) = x_1$ . For  $x_1 = 0$  so, we talk about exact null controllability.

# Relation between stabilizability and controllability

System (??) is said exponentially stabilizable, if there exists a linear feedback control  $u(t) = Dx(t)$ , where  $D$  another linear bounded operator such that

$$\|e^{A_0^{-1}(B+CD)t}\| \leq M_\omega e^{-\omega t}, \quad M_\omega \geq 1, \omega > 0. \quad (8)$$

The system (??) is said to be completely stabilizable if it is exponentially stabilizable for all  $\omega > 0$ .

Let  $\mathcal{R}_T$  be the reachability operator defined as

$$\mathcal{R}_T u(\cdot) = \int_0^T S(t-\tau)A_0^{-1}Cu(\tau)d\tau, \quad (9)$$

# Relation between stabilizability and controllability

which is a linear bounded operator acting from  $L_p$  to  $\mathcal{H}$ . The system (??) is exactly controllable if  $Im(\mathcal{R}_T) = \mathcal{H}$  also, it is exactly null controllable if and only if

$$Im(\mathcal{R}_T) \subset Im(e^{A_0^{-1}(B+CD)T}), \quad \forall T > 0.$$

We denote by  $\mathcal{R}_T^*$  the adjoint operator of  $\mathcal{R}_T$  satisfies the property:

$$\exists \delta > 0, \forall x^* \in \mathcal{H}, \|\mathcal{R}_T^* x^*\| \geq \delta \|x^*\|. \quad (10)$$

We can have many implicit conditions on exact controllability summarized by the bellow formulation:

$$\|\mathcal{R}_T^* x^*\| = \left( \int_0^T \|C^*(A_0^*)^{-1} S^*(t) x^*\|^q dt \right)^{\frac{1}{q}}, \quad u \in L_p, p > 1, \quad (11)$$

$$\|\mathcal{R}_T^* x^*\| = \text{ess sup} \{ \|C^*(A_0^*)^{-1} S^*(t) x^*\| \}, \quad 0 \leq t \leq T, u \in L_1;$$

where  $\text{ess sup}$  is the essential supremum of a set.

The condition of exact controllability in the class of controls  $L_p$ ,  $p > 1$  are equivalent but the situation become more complicated to show it in the class  $L_1$ .

## Theorem

[?, ?] The system (??) is exactly controllable in the class  $L_p$  if and only if

- For  $p = 1$ , if  $\lim_{n \rightarrow \infty} (C^*(A_0^*)^{-1}S^*(t)x_n^*) = 0$ , uniformly for all  $t \in [0, T]$  then  $\lim_{n \rightarrow \infty} x_n^* = 0$ .
- $p > 1$ , if  $\lim_{n \rightarrow \infty} (C^*(A_0^*)^{-1}S^*(t)x_n^*) = 0$ , for all  $t \in [0, T]$  then  $\lim_{n \rightarrow \infty} x_n^* = 0$ .

# Conclusion

The notion of stability and controllability of new class of controlled systems defined by implicit stationary differential equation was the purpose of this paper. In course of this work we used the spectral theory of the operator pencil  $\lambda A - B$  to provide conditions for the stability in sens of Lyapunov also we studied the controllability of those systems. Furthermore, most of researchs will be directed to open problems for some particular types of systems on special spaces with infinite dimension.

# References

-  Benabdallah, M. On the exponential stability of implicit systems in Banach spaces. *Chiers Math.de l'universit d'Oran.Fascicule1* **1989**, 2–12.
-  Doletski, Yu.L. and Krein, M.G. Stability of solutions of differential equations in Banach space. *American Math Society* **1974**.
-  Favini, A. and Yagi, A. Degenerate Differential Equations in Banach Spaces. *Marcel Dekker Inc* **1999**.
-  Gantmacher, F.R . In *Theory of matrices*; Dunod, 1965, vol. 1,2.
-  Olbrot, A.W, Pandofli. L. Null controllability of a class of functional differential systems. *Int. J. Control* **1988**, 193–208.
-  Rabah, R. Controllability of linear systems with constant delay in Banach spaces. *RAIRO Automat.-Prod. Inform. Ind* **1986**, 529–539.
-  Rutkas, A.G. Spectral methods for studying degenerate differential–operator equations. *J. Math. Sci* **2010**, 4246–4263.
-  Vlasenko, L.A. Evolutionary models with implicit and degenerate differential equations. *Dniepropetrovsk* **2006**.
-  Zabczyk, J. Mathematical Control theory: an introduction. *Systems & Control*: 

Thanks for your attention